

SPECIFICATION

TITLE OF THE INVENTION

Sealed Motor Compressor

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a sealed motor compressor constituted to contain a compressing element and an electromotive element for driving the compressing element in a sealed container.

As a conventional electromotive element for driving a sealed motor compressor constituting a freezing cycle of a refrigerator (freezer), or an air conditioner, an induction motor driven by a single-phase commercial power source, DC brushless motor, and the like have been employed. An electromotive element of the motor is fixed in a sealed container, and the electromotive element is constituted of a stator comprising a stator winding, and a rotor rotating in the stator. Moreover, the electromotive element supplies a commercial alternating current supply to the stator winding to induce/rotate the rotor.

However, the DC brushless motor requires a drive control equipment, and disadvantageously results in a cost increase. Moreover, since a secondary copper loss is theoretically present in the induction motor, running efficiency is limited. Therefore, there has been a desire for further improvement of the running efficiency of the

sealed motor compressor driven by the commercial single phase power source without using any control equipment.

Moreover, there has been a desire for development of the sealed motor compressor in which the electromotive element using a three-phase power source can be driven with a high efficiency without requiring any drive control equipment.

SUMMARY OF THE INVENTION

509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
2235
2236
2237
2238
2239
2240
2241
2242
2243
2244
2245
2246
2247
2248
2249
2250
2251
2252
2253
2254
2255
2256
2257
2258
2259
2260
2261
2262
2263
2264
2265
2266
2267
2268
2269
2270
2271
2272
2273
2274
2275
2276
2277
2278
2279
2280
2281
2282
2283
2284
2285
2286
2287
2288
2289
2290
2291
2292
2293
2294
2295
2296
2297
2298
2299
2300
2301
2302
2303
2304
2305
2306
2307
2308
2309
2310
2311
2312
2313
2314
2315
2316
2317
2318
2319
2320
2321
2322
2323
2324
2325
2326
2327
2328
2329
2330
2331
2332
2333
2334
2335
2336
2337
2338
2339
2340
2341
2342
2343
2344
2345
2346
2347
2348
2349
2350
2351
2352
2353
2354
2355
2356
2357
2358
2359
2360
2361
2362
2363
2364
2365
2366
2367
2368
2369
2370
2371
2372
2373
2374
2375
2376
2377
2378
2379
2380
2381
2382
2383
2384
2385
2386
2387
2388
2389
2390
2391
2392
2393
2394
2395
2396
2397
2398
2399
2400
2401
2402
2403
2404
2405
2406
2407
2408
2409
2410
2411
2412
2413
2414
2415
2416
2417
2418
2419
2420
2421
2422
2423
2424
2425
2426
2427
2428
2429
2430
2431
2432
2433
2434
2435
2436
2437
2438
2439
2440
2441
2442
2443
2444
2445
2446
2447
2448
2449
2450
2451
2452
2453
2454
2455
2456
2457
2458
2459
2460
2461
2462
2463
2464
2465
2466
2467
2468
2469
2470
2471
2472
2473
2474
2475
2476
2477
2478
2479
2480
2481
2482
2483
2484
2485
2486
2487
2488
2489
2490
2491
2492
2493
2494
2495
2496
2497
2498
2499
2500
2501
2502
2503
2504
2505
2506
2507
2508
2509
2510
2511
2512
2513
2514
2515
2516
2517
2518
2519
2520
2521
2522
2523
2524
2525
2526
2527
2528
2529
2530
2531
2532
2533
2534
2535
2536
2537
2538
2539
2540
2541
2542
2543
2544
2545
2546
2547
2548
2549
2550
2551
2552
2553
2554
2555
2556
2557
2558
2559
2560
2561
2562
2563
2564
2565
2566
2567
2568
2569
2570
2571
2572
2573
2574
2575
2576
2577
2578
2579
2580
2581
2582
2583
2584
2585
2586
2587
2588
2589
2590
2591
2592
2593
2594
2595
2596
2597
2598
2599
2600
2601
2602
2603
2604
2605
2606
2607
2608
2609
2610
2611
2612
2613
2614
2615
2616
2617
2618
2619
2620
2621
2622

Moreover, for the sealed motor compressor of the present invention, in the above, the electromotive element comprises a single-phase bipolar constitution.

Furthermore, for the sealed motor compressor of the present invention, in the above, the electromotive element is started by a system using a startup capacitor.

Sub. B4
Cov. 1.

Additionally, for the sealed motor compressor of the present invention, in addition to the above, the stator winding comprises a main winding and an auxiliary winding, and a winding ratio of the respective windings by effective winding number calculation is set to be in a range of 1.0 ± 0.5 .

Moreover, in the sealed motor compressor of the present invention, in addition to the aforementioned respective inventions, the squirrel-cage secondary conductor of the rotor comprises a skewed structure.

Furthermore, for the sealed motor compressor of the present invention, in the aforementioned respective inventions, the permanent magnet is a rare earth magnet.

Additionally, for the sealed motor compressor of the present invention, in the aforementioned respective inventions, the number of permanent magnets embedded in the rotor yoke is any number selected from the group consisting of two, four, six and eight.

Moreover, in addition to the aforementioned respective inventions, the sealed motor compressor of the present invention further comprises current-sensitive

protection means for detecting a line current.

Furthermore, according to the present invention, there is provided a sealed motor compressor constituted to contain a compressing element and an electromotive element for driving the compressing element in a sealed container. The electromotive element is driven by a three-phase power source, fixed to the sealed container, and constituted of a stator provided with a stator winding and a permanent magnet embedded type rotor which rotates in the stator. The rotor comprises a squirrel-cage secondary conductor disposed in a peripheral portion of a rotor yoke, and a permanent magnet embedded in the rotor yoke.

Moreover, for the sealed motor compressor of the present invention, in the above, the electromotive element comprises a three-phase bipolar constitution.

Furthermore, in the sealed motor compressor of the present invention, in addition to the aforementioned respective inventions, the squirrel-cage secondary conductor of the rotor comprises a skewed structure, and a skew pitch is more than 0, and is 1.5 slot pitches or less.

Additionally, for the sealed motor compressor of the present invention, in addition to the aforementioned respective inventions, the permanent magnet is a rare earth magnet.

Moreover, for the sealed motor compressor of the present invention, in addition to the aforementioned respective inventions, the number of permanent magnets

embedded in the rotor yoke is an even number.

Furthermore, in addition to the aforementioned respective inventions, the sealed motor compressor of the present invention further comprises current-sensitive protection means for detecting a line current.

Additionally, for the sealed motor compressor of the present invention, in addition to the aforementioned respective inventions, capability control is enabled.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a vertical side sectional view of a sealed motor compressor to which the present invention is applied.

Fig. 2 is a plan view of a rotor of the sealed motor compressor of Fig. 1.

Fig. 3 is a transverse top plan view of the rotor of the present invention.

Fig. 4 is an electric circuit diagram of an electromotive element (motor) constituting the sealed motor compressor of the present invention.

Fig. 5 is another transverse top plan view of the rotor of the present invention.

Fig. 6 is still another transverse top plan view of the rotor of the present invention.

Fig. 7 is still another transverse top plan view of the rotor of the present invention.

Fig. 8 is still another transverse top plan view of the rotor of the present invention.

Fig. 9 is still another transverse top plan view of the rotor of the present invention.

Fig. 10 is still another transverse top plan view of the rotor of the present invention.

Fig. 11 is still another transverse top plan view of the rotor of the present invention.

Fig. 12 is still another transverse top plan view of the rotor of the present invention.

Fig. 13 is a vertical side sectional view of the sealed motor compressor to which another present invention is applied.

Fig. 14 is a plan view of the rotor of the sealed motor compressor of Fig. 13.

Fig. 15 is a transverse top plan view of the rotor of Fig. 14.

Fig. 16 is an electric circuit diagram of the electromotive element (motor) constituting the sealed motor compressor of Fig. 13.

Fig. 17 is another transverse top plan view of the rotor of the present invention.

Fig. 18 is still another transverse top plan view of the rotor of the present invention.

Fig. 19 is still another transverse top plan view of the rotor of the present invention.

Fig. 20 is still another transverse top plan view of the rotor of the present invention.

Fig. 21 is still another transverse top plan view of

the rotor of the present invention.

Fig. 22 is still another transverse top plan view of the rotor of the present invention.

Fig. 23 is still another transverse top plan view of the rotor of the present invention.

Fig. 24 is still another transverse top plan view of the rotor of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Wh. 135
An embodiment of the present invention will next be described with reference to the drawings. Fig. 1 is a vertical side sectional view of a sealed motor compressor C to which the present invention is applied. In Fig. 1, in a sealed container 1, a motor (alternating current induction motor) 2 is contained as an electromotive element in an upper part of the container, and a compressing element 3 rotated/driven by the motor 2 is contained in a lower part of the container. The sealed container 1 is constituted by containing the motor 2 and compressing element 3 beforehand in two pre-divided sections, and hermetically closing the sections by high-frequency welding. Additionally, examples of the sealed motor compressor C include a rotary compressor, reciprocating compressor, and a scroll compressor.

The motor 2 is provided with a single-phase bipolar constitution, and constituted of a stator 4 fixed to an inner wall of the sealed container 1, and a rotor 5 supported inside the stator 4 to be freely rotatable centering on a

pub. B5 cond.
rotation shaft 6. Moreover, the stator 4 is provided with a stator winding 7 for supplying a rotary magnetic field to the rotor 5.

The compressing element 3 is provided with a first rotary cylinder 9 and second rotary cylinder 10 which are divided from each other by a middle partition plate 8. Eccentric parts 11, 12 rotated/driven by the rotation shaft 6 are attached to the respective cylinders 9, 10, and these eccentric parts 11, 12 deviate from each other in phase by 180 degrees.

NUMERALS 13, 14 denote first and second rollers rotating in the respective cylinders 9, 10, and the respective rollers rotate in the cylinders by rotation of the eccentric parts 11, 12. Numerals 15, 16 denote first and second frames, the first frame 15 forms a closed compression space of the cylinder 9 together with the middle partition plate 8, and the second frame 16 similarly forms the closed compression space of the cylinder 10 together with the middle partition plate 8. Moreover, the first and second frames 15, 16 are provided with bearings 17, 18 which rotatably support a lower part of the rotation shaft 6.

Discharge mufflers 19, 20 are attached to cover the first and second frame 15, 16, respectively. Additionally, the cylinder 9 and discharge muffler 19 are connected to each other via a discharge hole (not shown) disposed in the first frame 15, and the cylinder 10 and discharge muffler 20 are also connected to each other via a discharge hole (not shown)

disposed in the second frame 16. A bypass tube 21 is disposed on an outer part of the sealed container 1, and connected to the inside of the discharge muffler 20.

Moreover, numeral 22 denotes a discharge tube disposed on the top of the sealed container 1, and 23, 24 denote suction tubes connected to the cylinders 9, 10. Moreover, numeral 25 denotes a sealed terminal for supplying power to the stator winding 7 of the stator 4 from the outside of the sealed container 1 (a lead wire for connecting the sealed terminal 25 to the stator winding 7 is not shown).

Moreover, numeral 26 denotes a rotor core in which a plurality of rotor iron plates obtained by stamping 0.3 to 0.7 mm thick electromagnetic steel plates into predetermined shapes (not shown) are laminated and integrally caulked/laminated onto one another (additionally, the plates may integrally be welded to one another without being caulked). Numerals 66, 67 denote flat-plate end surface members attached to upper and lower ends of the rotor iron 26, and the members are molded of nonmagnetic materials such as aluminum and resin materials into substantially the same shapes as those of the rotor iron plates. A balance weight A is fixed to the rotor core 26 via the upper end surface member 66 by a rivet 51.

Sub. B6
Fig. 2 is a plan view of the rotor 5 shown in Fig. 1, and Fig. 3 is a transverse top plan view of the rotor 5. The rotor 5 is constituted of a rotor yoke 5A, squirrel-cage secondary conductor 5B disposed in a peripheral portion of

the rotor yoke 5A, and a permanent magnet 31 embedded in the rotor yoke 5A. A plurality of squirrel-cage secondary conductors 5B are disposed in the peripheral portion of the rotor yoke 5A, and the conductor is injection-molded in a cylindrical hole (not shown) formed in a squirrel-cage shape across an extending direction of the rotation shaft 6 by aluminum die casting. Both ends of the squirrel-cage secondary conductor 5B are formed in a so-called skewed structure such that each end is sloped in a spiral form with a predetermined angle in a circumferential direction of the rotation shaft 6.

Moreover, two permanent magnets 31 are embedded in the rotor yoke 5A. The permanent magnets 31 are formed in plate shapes, disposed opposite and parallel to each other centering on the rotor 5, and embedded from one end to the other end of the rotor yoke 5A. Used in the permanent magnet 31 is a rare earth magnet which has a highest magnetic flux density among permanent magnets. Opposite surfaces of the permanent magnets 31 are embedded with different magnetic poles. That is to say, the respective permanent magnets 31 are embedded toward the outside of the circumferential direction of the rotor 5 with different magnetic poles, and constituted such that a rotating force can be imparted to the rotor 5 with magnetic force lines of a main winding 7A and auxiliary winding 7B described later.

On the other hand, in Fig. 4, the motor (electromotive element) 2 is provided with the stator winding

7 comprising the main winding 7A and auxiliary winding 7B. The stator winding 7 is constituted of the main winding 7A and auxiliary winding 7B, and the winding ratio of the main winding 7A to the auxiliary winding 7B by effective winding number calculation is set to 1.0 ± 0.5 . Moreover, one end of the auxiliary winding 7B is connected to a running capacitor 32 connected in series, and a serial circuit of a startup capacitor 33 and startup switch 33A connected parallel to the running capacitor 32.

A power supply circuit of the stator winding 7 is provided with current-sensitive protection means 34 for detecting a line current, the protection means 34 is constituted of a line current detector 34B for detecting the line current, and a protection switch 34A, and the protection switch 34A is connected in series with the other end of the main winding 7A. Moreover, when the line current detector 34B senses a predetermined current, the line current detector 34B actuates the protection switch 34A in such a manner that power supply to the stator winding 7 can be cut off. Additionally, the protection switch 34A also serves as a power switch for controlling the power supply to the motor 2. In this case, a power switch (not shown) other than the protection switch 34A may be disposed in series with the protection switch 34A.

sub.
B7

Operation of the aforementioned constitution will next be described. Additionally, it is assumed that the motor 2 is stopped and the startup switch 33A is closed.

Moreover, when the power switch (protection switch 34A) is closed, current starts to flow to the main winding 7A and auxiliary winding 7B. Furthermore, since the auxiliary winding 7B is connected to a parallel circuit of the startup capacitor 33 and running capacitor 32, the rotor 5 obtains a required startup torque and starts in a predetermined rotation direction.

In this case, since the rotor 5 has a squirrel-cage secondary conductor similar to a general induction machine, the rotor 5 responds to the current flowing to the stator winding 7 and the motor 2 is started. Moreover, when the rotor 5 is accelerated to achieve rotation at a predetermined number of revolutions (in this case, about 80% of the number of synchronous revolutions), the startup switch 33A is opened to disconnect the startup capacitor 33 from the circuit, and the motor 2 is operated only by the running capacitor 32. Thereby, during a transient state of the motor 2 from a startup moment at which the power switch closes until the motor enters synchronous running, it is possible to generate a torque larger than a braking torque generated by the permanent magnet 31. Therefore, during self starting, the surpassing large torque is generated and the motor can be started.

Moreover, since the squirrel-cage secondary conductor 5B of the rotor 5 is provided with the skewed structure, similarly as the conventional induction motor, self starting can easily be performed with the single phase

power source. Moreover, since the synchronous running can be secured by the permanent magnet 31, secondary copper loss during running can largely be decreased.

On the other hand, during running of the motor 2, the line current detector 34B monitors the current flowing through the stator winding 7, and it is possible to cut off the power supply to the motor 2 when the rotor 5 generates heat. That is, when the rotor 5 generates heat, the protection means 34 cuts off the current flowing through the stator winding 7, and prevents the rotor 5 from further raising its temperature. This can prevent the permanent magnet 31 embedded in the rotor 5 from being demagnetized by heat (demagnetization by temperature). Additionally, since demagnetization by a predetermined temperature added to the permanent magnet 31 is a conventional known technique, detailed description thereof is omitted.

As described above, since in the rotor 5 of the motor 2 provided with the single-phase bipolar constitution, the permanent magnets 31 are embedded in the squirrel-cage secondary conductor 5B disposed in the peripheral portion of the rotor yoke 5A, and the rotor yoke 5A, the self starting can be performed even in the single-phase bipolar constitution similarly as the conventional induction motor. Additionally, during running, the synchronous running can be secured by the action of the embedded permanent magnet 31, the braking torque generated during the transient state from the starting until the synchronous running raises no problem,

and the secondary copper loss during running can largely be reduced.

Moreover, since the winding ratio of the main winding 7A to the auxiliary winding 7B by the effecting winding number calculation, a stator winding structure can remain to be the single-phase bipolar structure similarly as the conventional induction motor. This obviates the necessity of additional equipment such as changing of the equipment associated with manufacturing of the stator. Additionally, a running capacitor capacity can be matched to largely improve the running efficiency.

Furthermore, since the squirrel-cage secondary conductor 5B is provided with the skewed structure, similarly as the conventional induction motor, it is possible to easily perform self starting with the single phase power source. This allows the motor 2 to easily perform the self starting even with the single phase power source. Moreover, since the permanent magnet 31 is formed of a rare earth magnet, it is possible to remarkably increase the magnetic flux density of the permanent magnet 31.

Moreover, since two, four, six, or eight permanent magnets 31 are embedded in the rotor yoke 5A, it is possible to set the number of permanent magnets 21 in accordance with a purpose of the motor 2 for use. Furthermore, since the power supply circuit of the stator winding 7 is provided with the current sensitive protection means 34 for detecting the line current, during heating of the rotor 5, the power supply

Sub.
B-7
Cond

to the motor 2 can be cut off to suppress the temperature rise of the rotor 5. This can prevent the permanent magnet 31 embedded in the rotor 5 from causing the temperature demagnetization by the heat.

Next, Fig. 5 shows another rotor 5 in which two permanent magnets 31 are embedded into the rotor yoke 5A. In this case, the permanent magnets 31 are embedded inside the squirrel-cage secondary conductors 5B in circular arc shapes with a predetermined interval close to each other, and each permanent magnet 31 is embedded to extend from one end to the other end of the rotor yoke 5A. Both permanent magnets 31 are embedded toward the outside of the circumferential direction of the rotor 5 with different magnetic poles.

Moreover, Figs. 6, 7, and 8 shows another rotor 5 in which four permanent magnets 31 are embedded in the rotor yoke 5A. In Fig. 6, the permanent magnets 31 are embedded inside the squirrel-cage secondary conductors 5B, two of the permanent magnets 31 are arranged substantially in a V shape and opposite to the other pair of the magnets centering on the rotor 5, and the magnets are arranged substantially in a vertically long rhombus shape. Additionally, each permanent magnet 31 is embedded to extend from one end to the other end of the rotor yoke 5A. Moreover, in Fig. 7, the permanent magnets 31 are embedded inside the squirrel-cage secondary conductors 5B, and two of the permanent magnets 31 are arranged substantially in a square shape and opposite to the other pair of the magnets centering on the rotor 5 to obtain

a substantially square arrangement. Additionally, each permanent magnet 31 is embedded to extend from one end to the other end of the rotor yoke 5A.

Moreover, in Fig. 8, two permanent magnets 31 formed in plate shapes are embedded in the vicinity of the rotation shaft 6, and parallel to these magnets 31, the other magnets are embedded with a predetermined interval on the side of the squirrel-cage secondary conductors 5B. One pair of permanent magnets 31 are embedded opposite to the other pair centering on the rotation shaft 6, and four permanent magnets 31 in total are embedded to extend from one end to the other end of the rotor yoke 5A. Moreover, the respective permanent magnets 31 embedded opposite to each other centering on the rotor 5 are embedded with different magnetic poles toward the outside of the circumferential direction of the rotor 5 centering on the rotation shaft 6. That is, when four permanent magnets 31 are embedded opposite to each other centering on the rotation shaft 6, a magnetic force of the permanent magnet 31 is increased. This can realize a further large running efficiency and power factor.

Furthermore, Figs. 9 and 10 show another rotor 5 in which six permanent magnets 31 are embedded in the rotor yoke 5A. In Fig. 9, the permanent magnets 31 are arranged in a hexagonal shape inside the squirrel-cage secondary conductors 5B. Moreover, in Fig. 10, four permanent magnets 31 are embedded in the state of Fig. 7, and the permanent magnets 31 are embedded in centers of and substantially at right angles

to the opposite permanent magnets 31. The permanent magnets 31 embedded substantially at right angles are embedded on departing sides of the opposite permanent magnets 31, and the respective permanent magnets 31 are embedded to extend from one end to the other end of the rotor yoke 5A. Moreover, the respective permanent magnets 31 embedded opposite to each other centering on the rotor 5 are embedded with different magnetic poles toward the outside of the circumferential direction of the rotor 5 centering on the rotation shaft 6. That is, six permanent magnets 31 are embedded opposite to each other centering on the rotation shaft 6 to increase the magnetic force of the permanent magnet 31.

Additionally, Figs. 11 and 12 show another rotor 5 in which eight permanent magnets 1 are embedded in the rotor yoke 5A. In Fig. 11, the permanent magnets 31 are arranged in an octagonal shape inside the squirrel-cage secondary conductors 5B, and the respective permanent magnets 31 are embedded to extend from one end to the other end of the rotor yoke 5A. Moreover, in Fig. 12, eight permanent magnets 31 are embedded in the state of Fig. 7, and two permanent magnets 31 are embedded parallel to each other in the center of and substantially at right angles to the opposite permanent magnet 31. Two permanent magnets 31 embedded substantially at right angles are embedded on the departing sides of the opposite permanent magnets 31, and the respective permanent magnets 31 are embedded to extend from one end to the other end of the rotor yoke 5A. Moreover, the

respective permanent magnets 31 embedded opposite to each other centering on the rotor 5 are embedded with different magnetic poles toward the outside of the circumferential direction of the rotor 5 centering on the rotation shaft 6. That is, eight permanent magnets 31 are embedded opposite to each other centering on the rotation shaft 6 to further increase the magnetic force of the permanent magnet 31. In this manner, when a plurality of magnets are disposed, much more running efficiency and power factor can be realized.

As described above in detail, according to the present invention, the electromotive element is fixed to the sealed container, and is constituted of the stator provided with the stator winding and the rotor rotating in the stator, and the rotor is constituted of the squirrel-cage secondary conductor disposed in the peripheral portion of the rotor yoke, and the permanent magnet embedded in the rotor yoke. Therefore, the electromotive element can be allowed to self-start even with the single-phase bipolar constitution similarly as the conventional induction motor. Moreover, during running, the synchronous running can be secured by the action of the embedded permanent magnet. This can largely decrease the secondary copper loss during running. Therefore, the running efficiency and power factor of the electromotive element can largely be enhanced.

Moreover, according to the present invention, in addition to this, the electromotive element is started by the system in which the startup capacitor is used. Therefore,

during the transient state of the electromotive element from the starting until the synchronous running, a large braking torque is generated by the permanent magnet, but during self starting, a surpassing large torque can be generated. Therefore, even when load is large during starting, the electromotive element can remarkably easily be started.

Furthermore, according to the present invention, in addition to the above, the stator winding comprises the main and auxiliary windings, and the winding ratio of the respective windings by the effective winding number calculation is set to 1.0 ± 0.5 . Therefore, the stator winding structure can remain to be a single-phase bipolar structure similarly as the conventional induction motor. This obviates the necessity of additional equipment such as the equipment change associated with manufacturing of the stator. Particularly, when the effective winding number ratio of the main winding to the auxiliary winding of the stator is set to 1.0 ± 0.5 , and the running capacitor capacity is matched, the running efficiency can largely be improved.

Additionally, according to the present invention, in addition to the above, since the rotor squirrel-cage secondary conductor is provided with the skewed structure, for example, similarly as the conventional induction motor, the self starting can easily be performed even with the single phase power source. Therefore, the electromotive element can easily self-start even with the single phase

power source and is remarkably practically effective.

Moreover, according to the present invention, in addition to the above, since the permanent magnet is a rare earth magnet, the magnetic flux density of the permanent magnet embedded in the rotor yoke can largely be increased. This can achieve a remarkably high running efficiency during synchronous running. Therefore, power consumption can largely be reduced.

Furthermore, according to the present invention, in addition to the above, since the number of permanent magnets embedded in the rotor yoke is any number of two, four, six and eight, it is possible to set the number of permanent magnets in accordance with the purpose. Therefore, general-purpose properties can largely be enlarged.

Additionally, according to the present invention, in addition to the above, since the current sensitive protection means for detecting the line current is disposed, it is possible to cut off the power supply to the electromotive element during heating of the rotor and suppress the temperature rise of the rotor. This can prevent the temperature demagnetization by the heat of the permanent magnet embedded in the rotor beforehand. Therefore, even when a large load or a large current flows through the rotor conductor to generate heat during running of the electromotive element, the temperature demagnetization of the permanent magnet can securely be prevented, and the reliability of the electromotive element can largely be

enhanced.

Another embodiment of the present invention will next be described with reference to Fig. 13 to 24. Fig. 13 is a vertical side sectional view of the sealed motor compressor C to which the present invention is applied. In Fig. 13, in a sealed container 101, a motor (alternating current induction motor) 102 is contained as the electromotive element in the upper part of the container, and a compressing element 103 rotated/driven by the motor 102 is contained in the lower part of the container. The sealed container 101 is constituted by containing the motor 102 and compressing element 103 beforehand in two pre-divided sections, and hermetically closing the sections by high-frequency welding. Additionally, examples of the sealed motor compressor C include a rotary compressor, reciprocating compressor, and scroll compressor.

The motor 102 is provided with a three-phase bipolar constitution, and constituted of a stator 104 fixed to the inner wall of the sealed container 101, and a rotor 105 supported inside the stator 104 to be freely rotatable centering on a rotation shaft 106. Moreover, a stator iron core 104A of the stator 104 is provided with a stator winding 107 for supplying a rotary magnetic field to the rotor 105.

The compressing element 103 is provided with a first rotary cylinder 109 and second rotary cylinder 110 which are divided from each other by a middle partition plate 108. Eccentric parts 111, 112 rotated/driven by the rotation shaft

106 are attached to the respective cylinders 109, 110, and these eccentric parts 111, 112 deviate from each other in phase by 180 degrees.

Numerals 113, 114 denote first and second rollers rotating in the respective cylinders 109, 110, and the respective rollers rotate in the cylinders by rotation of the eccentric parts 111, 112. Numerals 115, 116 denote first and second frames, the first frame 115 forms a closed compression space of the cylinder 109 together with the middle partition plate 108, and the second frame 116 similarly forms the closed compression space of the cylinder 110 together with the middle partition plate 108. Moreover, the first and second frames 115, 116 are provided with bearings 117, 118 which rotatably support the lower part of the rotation shaft 106.

Discharge mufflers 119, 120 are attached to cover the first and second frame 115, 116, respectively. Additionally, the cylinder 109 and discharge muffler 119 are connected to each other via the discharge hole (not shown) disposed in the first frame 115, and the cylinder 110 and discharge muffler 120 are also connected to each other via the discharge hole (not shown) disposed in the second frame 116. A bypass tube 121 is disposed on the outer part of the sealed container 101, and connected to the inside of the discharge muffler 120.

Moreover, numeral 122 denotes a discharge tube disposed on the top of the sealed container 101, and 123, 124

denote suction tubes connected to the cylinders 109, 110. Moreover, numeral 125 denotes a sealed terminal for supplying power to the stator winding 107 of the stator 104 from the outside of the sealed container 101 (the lead wire for connecting the sealed terminal 125 to the stator winding 107 is not shown).

Moreover, numeral 126 denotes a rotor core in which a plurality of rotor iron plates obtained by stamping 0.3 to 0.7 mm thick electromagnetic steel plates into predetermined shapes (not shown) are laminated and integrally caulked/laminated onto one another (additionally, the plates may integrally be welded to one another without being caulked). Numerals 166, 167 denote flat-plate end surface members attached to upper and lower ends of the rotor iron core 126, and the members are molded of nonmagnetic materials such as aluminum and resin materials into substantially the same shapes as those of the rotor iron plates. A balance weight A is fixed to the rotor iron core 126 via the upper end surface member 166 by a rivet 151.

Fig. 14 is a plan view of the rotor 105 shown in Fig. 13, and Fig. 15 is a transverse top plan view of the rotor 105. The rotor 105 is constituted of a rotor yoke 105A, squirrel-cage secondary conductor 105B disposed in the peripheral portion of the rotor yoke 105A, and a permanent magnet 131 embedded in the rotor yoke 105A. A plurality of squirrel-cage secondary conductors 105B are disposed in the peripheral portion of the rotor yoke 105A, and the conductor

is injection-molded in a cylindrical hole (not shown) formed in the squirrel-cage shape across the extending direction of the rotation shaft 106 by aluminum die casting. Both ends of the squirrel-cage secondary conductor 105B are formed in a so-called skewed structure such that each end is sloped in a spiral form with a predetermined angle in a circumferential direction of the rotation shaft 106. The squirrel-cage secondary conductor 105B is constituted in a skew which is more than 0 and is 1.5 slot pitches or less. The 0 slot pitch means a state in which one-end slot of the squirrel-cage secondary conductor is vertically extended to the other end along the extending direction of the rotation shaft, and 1.5 slot pitches mean a state in which one-end slot is twisted by 1.5 slots toward the other end in a circumferential direction. That is to say, the skew is constituted between 0 and 1.5 slot pitches.

Moreover, two permanent magnets 131 are embedded in the rotor yoke 105A. The permanent magnets 131 are formed in plate shapes, disposed opposite and parallel to each other centering on the rotor 105, and embedded from one end to the other end of the rotor yoke 105A. Used in the permanent magnet 131 is a rare earth magnet which has a highest magnetic flux density among permanent magnets. Opposite surfaces of the permanent magnets 131 are embedded with different magnetic poles. That is to say, the respective permanent magnets 131 are embedded toward the outside of the circumferential direction of the rotor 105 with different

magnetic poles, and constituted such that the rotating force can be imparted to the rotor 105 with the magnetic force lines of respective windings 107A, 107B, and 107C described later.

On the other hand, in Fig. 16, the motor (electromotive element) 102 is provided with the three-phase stator winding 107 comprising the windings 107A, 107B, and 107C. The stator winding 107 is constituted of the windings 107A, 107B, and 107C, and the windings 107A, 107B, and 107C are connected to a three-phase alternating commercial power supply AC via a power switch 133.

The power supply circuit of the stator winding 107 is provided with current-sensitive protection means 134 for detecting the line current, the protection means 134 is constituted of a line current detector 134A for detecting the line current, and a protection switch. In this case, the power switch 133 also serves as the protection switch. That is to say, the motor 102 is protected in a current-sensitive CT control system. Moreover, when the line current detector 134A senses a predetermined current, the line current detector 134A actuates the protection switch (power switch 133) in such a manner that power supply to the stator winding 107 can be cut off. Additionally, a protection switch (not shown) other than the power switch 133 may be disposed in series with the power switch 133.

Operation of the aforementioned constitution will next be described. When the power switch 133 is closed,

three-phase current starts to flow to the windings 107A, 107B, and 107C, and the rotor 105 starts in the predetermined rotation direction. In this case, since the rotor 105 has a squirrel-cage secondary conductor 105B similar to a general induction machine, the rotor 105 responds to the current flowing to the stator winding 107 and the motor 102 is started.

In this case, since a three-phase sine wave alternating current (three-phase alternating commercial power supply AC) is applied to the stator winding 107, the rotor 105 of the motor 102 can perform self-starting similarly as the conventional induction synchronous electromotive element, and can perform synchronous running by the action of the embedded permanent magnet 131 during running.

Moreover, two permanent magnets 131 are embedded in the rotor yoke 105A, and the squirrel-cage secondary conductor 105B of the rotor 105 is provided with the structure of the skew more than 0 and 1.5 slot pitches or less. Thereby, during the transient state of the motor 102 from the startup moment at which the power switch 133 closes until the motor enters the synchronous running, it is possible to generate a torque larger than a braking torque generated by the permanent magnet 131. Therefore, similarly as the conventional induction electromotive element, the synchronous running can easily be performed with the three-phase alternating commercial power supply AC, and the secondary copper loss during running can largely be decreased.

On the other hand, during running of the motor 102, the line current detector 134A monitors the current flowing through the stator winding 107, and it is possible to cut off the power supply to the motor 102 when the rotor 105 generates heat. That is, when the rotor 105 generates heat, the protection means 134 cuts off the current flowing through the stator winding 107, and prevents the rotor 105 from further raising its temperature. This can prevent the permanent magnet 131 embedded in the rotor 105 from being demagnetized by heat (demagnetization by temperature). Additionally, since demagnetization by the predetermined temperature added to the permanent magnet 131 is a conventional known technique, detailed description thereof is omitted.

As described above, in the rotor 105 of the motor 102 provided with the three-phase bipolar constitution, the permanent magnets 131 are embedded in the squirrel-cage secondary conductor 105B disposed in the peripheral portion of the rotor yoke 105A, and the rotor yoke 105A. Moreover, the squirrel-cage secondary conductor 105B of the rotor 105A is structured such that the skew is more than 0 and is 1.5 slot pitches or less. Therefore, the self starting can be performed even in the three-phase bipolar constitution similarly as the conventional induction motor. Additionally, during running, the synchronous running can be secured by the action of the embedded permanent magnet 131. Therefore, the braking torque generated during the transient state from the

starting until the synchronous running raises no problem, and the secondary copper loss during running can largely be reduced.

Moreover, in the embodiment, the winding (windings 107A, 107B, 107C) of the stator 104 is constituted similarly as the conventional induction motor, and the motor 102 is provided with the three-phase bipolar structure. This obviates the necessity of additional equipment such as changing of the equipment associated with manufacturing of the stator 104. Additionally, the running efficiency can largely be improved.

On the other hand, a compression volume, and the like of the sealed motor compressor C is adjusted in accordance with a necessary capability. Even when a running load changes, running is possible in a high efficiency/power factor. This can largely improve the power factor and efficiency entirely during light load and overload. Moreover, a change of power factor/efficiency by a load fluctuation can largely be reduced.

Next, Table 1 shows an example of comparison of the conventional induction motor with the motor 102 of the present invention (referred to as the induction synchronous motor in the table) in the power factor and efficiency during usual running and during power control running. Additionally, it is assumed that the load during usual running is 3.0 N•m, and the load during the power control running is 1.5 N•m.

[Table 1]

	Usual running *running load:3.0N•m	Power control running *running load:1.5N•m
Induction motor		
Power factor (%)	84.5	72.2
Efficiency (%)	87.0	88.3
Induction synchronous motor		
Power factor (%)	95.0 (+9.6%)	92.9 (+20.7%)
Efficiency (%)	91.1	91.7

As described above, the synchronous running is secured during running of the motor 102, and the secondary copper loss largely decreases, so that the efficiency and power factor can largely be improved.

Moreover, in the conventional induction motor, the power factor of the light-load running is extremely lowered. In the motor 102 of the present invention, however, since the permanent magnet 131 is formed of a rare earth magnet, a high power factor running is possible from the light load to the overload. This can largely reduce the change amount of the power factor/efficiency by the load fluctuation, and the power factor/efficiency can largely be improved.

Next, Fig. 17 shows another rotor 105 in which two permanent magnets 131 are embedded into the rotor yoke 105A. In this case, the permanent magnets 131 are embedded inside the squirrel-cage secondary conductors 105B in circular arc shapes with a predetermined interval close to each other, and each permanent magnet 131 is embedded to extend from one end

to the other end of the rotor yoke 105A. Both permanent magnets 131 are embedded toward the outside of the circumferential direction of the rotor 105 with different magnetic poles.

Moreover, Figs. 18, 19, and 20 show another rotor 105 in which four permanent magnets 131 are embedded in the rotor yoke 105A. In Fig. 18, the permanent magnets 131 are embedded inside the squirrel-cage secondary conductors 105B, two of the permanent magnets 131 are arranged substantially in a V shape and opposite to the other pair of the magnets centering on the rotor 105, and the magnets are arranged substantially in a vertically long rhombus shape. Additionally, each permanent magnet 131 is embedded to extend from one end to the other end of the rotor yoke 105A. Moreover, in Fig. 19, the permanent magnets 131 are embedded inside the squirrel-cage secondary conductors 105B, and two of the permanent magnets 131 are arranged substantially in a square shape and opposite to the other pair of the magnets centering on the rotor 105 to obtain a substantially square arrangement. Additionally, each permanent magnet 131 is embedded to extend from one end to the other end of the rotor yoke 105A.

Moreover, in Fig. 20, two permanent magnets 131 formed in plate shapes are embedded in the vicinity of the rotation shaft 106, and parallel to these magnets 131, the other magnets are embedded with a predetermined interval on the side of the squirrel-cage secondary conductors 105B. One

pair of permanent magnets 131 are embedded opposite to the other pair centering on the rotation shaft 106, and four permanent magnets 131 in total are embedded to extend from one end to the other end of the rotor yoke 105A. Moreover, the respective permanent magnets 131 embedded opposite to each other centering on the rotor 105 are embedded with different magnetic poles toward the outside of the circumferential direction of the rotor 105 centering on the rotation shaft 106. That is, when four permanent magnets 131 are embedded opposite to each other centering on the rotation shaft 106, the magnetic force of the permanent magnet 131 is increased. This can realize a further large running efficiency and power factor.

Furthermore, Figs. 21 and 22 show another rotor 105 in which six permanent magnets 131 are embedded in the rotor yoke 105A. In Fig. 21, the permanent magnets 131 are arranged in a hexagonal shape inside the squirrel-cage secondary conductors 105B, and each permanent magnet 131 is embedded to extend from one end to the other end of the rotor yoke 105A. Moreover, in Fig. 22, four permanent magnets 131 are embedded in the state of Fig. 19, and the permanent magnets 131 are embedded in centers of and substantially at right angles to the opposite permanent magnets 131. The permanent magnets 131 embedded substantially at right angles are embedded on departing sides of the opposite permanent magnets 131, and the respective permanent magnets 131 are embedded to extend from one end to the other end of the rotor

yoke 105A. Moreover, the respective permanent magnets 131 embedded opposite to each other centering on the rotor 105 are embedded with different magnetic poles toward the outside of the circumferential direction of the rotor 105 centering on the rotation shaft 106. That is, six permanent magnets 131 are embedded opposite to each other centering on the rotation shaft 106 to increase the magnetic force of the permanent magnet 131.

Additionally, Figs. 23 and 24 show another rotor 105 in which eight permanent magnets 131 are embedded in the rotor yoke 105A. In Fig. 23, the permanent magnets 131 are arranged in an octagonal shape inside the squirrel-cage secondary conductors 105B, and the respective permanent magnets 131 are embedded to extend from one end to the other end of the rotor yoke 105A. Moreover, in Fig. 24, eight permanent magnets 131 are embedded in the state of Fig. 19, and two permanent magnets 131 are embedded parallel to each other in the center of and substantially at right angles to the opposite permanent magnet 131. Two permanent magnets 131 embedded substantially at right angles are embedded on the departing sides of the opposite permanent magnets 131, and the respective permanent magnets 131 are embedded to extend from one end to the other end of the rotor yoke 105A. Moreover, the respective permanent magnets 131 embedded opposite to each other centering on the rotor 105 are embedded with different magnetic poles toward the outside of the circumferential direction of the rotor 105 centering on

the rotation shaft 106. That is, eight permanent magnets 131 are embedded opposite to each other centering on the rotation shaft 106 to further increase the magnetic force of the permanent magnet 131. In this manner, when a plurality of magnets are disposed, much more running efficiency and power factor can be realized.

As described above, when two, four, six or eight permanent magnets 131 are embedded in the rotor yoke 105A, the number of the permanent magnets 131 can be set in accordance with the purpose of the motor 102. This secures the synchronous running during running of the motor 102 and reduces the secondary copper loss, and can thereby largely improve the efficiency and power factor.

Moreover, since the skew of the rotor 105 (squirrel-cage secondary conductor 105B) is set to more than 0, and 1.5 slot pitches or less, the skew of the squirrel-cage secondary conductor can be constituted to be optimum. That is, when the skew is 0, the secondary copper loss can most be decreased, so that an optimum efficiency can be obtained. On the other hand, when the skew is more than 0, and 1.5 slot pitches or less, cogging properties during one rotation is reduced, and starting torque can be enhanced. Therefore, similarly as the conventional induction electromotive element, the general characteristics can be optimized.

Particularly, the motor 102 can operate with from the light load to the overload at a high power factor and efficiency. Therefore, the change amount of the power

factor/efficiency by the load fluctuation can largely be reduced, and the power factor/efficiency can largely be improved entirely from the light load to the overload.

As described above, according to the present invention, the electromotive element driven by the three-phase power source is fixed to the sealed container, and is constituted of the stator provided with the stator winding and the rotor rotating in the stator, and the rotor is constituted of the squirrel-cage secondary conductor disposed in the peripheral portion of the rotor yoke, and the permanent magnet embedded in the rotor yoke. Therefore, the electromotive element can be allowed to self-start similarly as the conventional induction motor. Moreover, during running, the synchronous running can be performed by the action of the embedded permanent magnet. Since the synchronous running is secured during running of the electromotive element, the secondary copper loss is decreased during running. Therefore, the efficiency and power factor of the electromotive element can largely be enhanced.

Moreover, since the stator winding is structured similarly as the conventional induction motor, and the three-phase bipolar structure is used, any specially additional equipment is unnecessary. Therefore, the equipment change associated with the stator structure is unnecessary, and the manufacturing cost increase of the electromotive element can be prevented.

Furthermore, since the rotor squirrel-cage secondary

conductor is provided with the skewed structure, and the skew pitch is set to more than 0, and 1.5 slot pitches or less, the optimum skew of the squirrel-cage secondary conductor can be constituted. That is, when the skew is 0, the secondary copper loss can most be decreased, and the optimum efficiency can be obtained. On the other hand, when the skew is more than 0, and 1.5 slot pitches or less, the cogging properties during one rotation can be lowered, and the starting torque can be enhanced. Therefore, similarly as the conventional induction motor, the entire characteristics can be optimized.

Moreover, since the permanent magnet is a rare earth magnet, a high efficiency can be obtained during synchronous running. This can largely improve the power factor/efficiency. Therefore, the power consumption of the sealed motor compressor can largely be reduced.

Furthermore, since the number of permanent magnets embedded in the rotor yoke is any even number, it is possible to set the number of permanent magnets in accordance with the purpose. Therefore, general-purpose properties can largely be enlarged.

Additionally, since the current sensitive protection means for detecting the line current is disposed, it is possible to cut off the power supply to the electromotive element during much heating of the rotor and to suppress the temperature rise of the rotor. This can securely prevent the temperature demagnetization by the heat of the rare earth magnet embedded in the rotor. Therefore, even when a large

current flows through the rotor conductor to generate heat during running of the electromotive element, the temperature demagnetization of the permanent magnet can securely be prevented, and the reliability of the electromotive element can largely be enhanced.

Moreover, since capability control is possible, the compression volume, and the like of the compressor is adjusted in accordance with a necessary capability during controlled running. Even when the running load changes, the running can be performed at the high efficiency/power factor.

Especially, in the ordinary induction electromotive element, the power factor during light-load running with controlled capability is excessively lowered. In the electromotive element of the present invention, however, high power factor running is possible with from the light load to the overload. This can largely reduce the change amount of the power factor/efficiency by the load fluctuation. Therefore, the power factor/efficiency can largely be improved.